

Powered by Universal Speech Solutions LLC



Yandex SS Plugin

Usage Guide

Revision: 1

Created: November 19, 2018

Last updated: November 19, 2018

Author: Arsen Chaloyan

Table of Contents

1	Overview.....	4
1.1	Installation	4
1.2	Applicable Versions.....	4
2	Supported Features.....	5
2.1	MRCP Methods	5
2.2	MRCP Events	5
2.3	MRCP Header Fields	5
2.4	Speech Data	5
3	Supported Voices	6
4	Configuration Format.....	7
4.1	Document.....	7
4.2	Synthesis Settings	8
4.3	Waveform Manager	9
4.4	SDR Manager	10
4.5	Monitoring Agent	11
4.6	Usage Change Handler	11
4.7	Usage Refresh Handler	12
4.8	License Server.....	12
5	Configuration Steps	15
5.1	Using Default Configuration.....	15
5.2	Specifying Folder ID	15
5.3	Specifying Synthesis Language	15
5.4	Specifying Sampling Rate.....	15
5.5	Specifying Voice Parameters.....	15
5.6	Specifying Prosody Parameters	15
5.7	Specifying Speech Data	16
5.8	Maintaining Waveforms	16
5.9	Maintaining Synthesis Details Records	16
6	Monitoring Usage Details	18
6.1	Log Usage	18
6.2	Update Usage.....	18
6.3	Dump Channels.....	19
7	Usage Examples.....	20
7.1	Plain Text.....	20
8	Sequence Diagram	21

9 References..... 22

 9.1 Yandex SpeechKit 22

 9.2 Specifications..... 22

1 Overview

This guide describes how to configure and use the Yandex Speech Synthesis (SS) plugin to the UniMRCP server. The document is intended for users having a certain knowledge of Yandex SpeechKit Text-to-Speech API and UniMRCP.



1.1 Installation

For installation instructions, use one of the guides below.

- RPM Package Installation (Red Hat / Cent OS)
- Deb Package Installation (Debian / Ubuntu)

1.2 Applicable Versions

Instructions provided in this guide are applicable to the following versions.



UniMRCP 1.6.0 and above

UniMRCP Yandex SS Plugin 1.0.0 and above

2 Supported Features

This is a brief check list of the features currently supported by the UniMRCP server running with the Yandex SS plugin.

2.1 MRCP Methods

- ✓ SPEAK
- ✓ STOP
- ✓ PAUSE
- ✓ RESUME
- ✓ BARGE-IN-OCCURRED
- ✓ SET-PARAMS
- ✓ GET-PARAMS

2.2 MRCP Events

- ✓ SPEECH-MARKER
- ✓ SPEAK-COMPLETE

2.3 MRCP Header Fields

- ✓ Kill-On-Barge-In
- ✓ Completion-Cause
- ✓ Voice-Gender
- ✓ Voice-Name
- ✓ Prosody-Rate
- ✓ Prosody-Volume
- ✓ Speech-Language

2.4 Speech Data

- ✓ Plain text (text/plain)

3 Supported Voices

All the voices supported by Yandex Text-to-Speech API are listed in the following page:

https://cloud.yandex.ru/docs/speechkit/tts/request#body_params

4 Configuration Format

The configuration file of the Yandex SS plugin is located in `/opt/unimrcp/conf/umsyandexss.xml`. The configuration file is written in XML.

4.1 Document

The root element of the XML document must be `<umsyandexss>`.

Attributes

Name	Unit	Description
license-file	File path	Specifies the license file. File name may include patterns containing '*' sign. If multiple files match the pattern, the most recent one gets used.
subscription-key-file	File path	Specifies the Yandex SpeechKit subscription key file to use. File name may include patterns containing '*' sign. If multiple files match the pattern, the most recent one gets used.

Parent

None.

Children

Name	Unit	Description
<code><synth-settings></code>	String	Specifies synthesis parameters.
<code><waveform-manager></code>	String	Specifies parameters of the waveform manager.
<code><sdr-manager></code>	String	Specifies parameters of the Synthesis Details Record (SDR) manager.
<code><monitoring-agent></code>	String	Specifies parameters of the monitoring manager.
<code><license-server></code>	String	Specifies parameters used to connect to the license server. The use of the license server is optional.

Example

This is an example of a bare document.

```
<umsyandexss license-file="umsyandexss_*.lic" subscription-key-file="yandex.subscription.key">
</ umsyandexss>
```

4.2 Synthesis Settings

This element specifies synthesis parameters.

Attributes

Name	Unit	Description
folder-id	String	Specifies the Yandex SpeechKit folder identifier. Required.
language	String	Specifies the default language to use, if not set by the client.
voice-name	String	Specifies the default voice name. Can be overridden by client.
emotion	String	Specifies an emotion, which can be set to either "good", "evil" or "neutral".
auth-validation-period	Integer	Specifies a period in seconds used to re-validate access token based on credentials.

Parent

```
<umsyandexss>
```

Children

None.

Example

This is an example of synthesis parameters.

```
<synth-settings
  folder-id="abcd1234edfg"
  language="en-US"
  voice-name=""
  emotion=" "
  auth-validation-period="3600"
```



```
</>
```

4.3 Waveform Manager

This element specifies parameters of the waveform manager.

Attributes

Name	Unit	Description
save-waveforms	Boolean	Specifies whether to save waveforms or not.
purge-existing	Boolean	Specifies whether to delete existing records on start-up.
max-file-age	Time interval [min]	Specifies a time interval in minutes after expiration of which a waveform is deleted. Set 0 for infinite.
max-file-count	Integer	Specifies the max number of waveforms to store. If reached, the oldest waveform is deleted. Set 0 for infinite.
waveform-folder	Dir path	Specifies a folder the waveforms should be stored in.

Parent

```
< umsyandexss >
```

Children

None.

Example

The example below defines a typical utterance manager having the default parameters set.

```
<waveform-manager  
  save-waveforms="false"  
  purge-existing="false"  
  max-file-age="60"  
  max-file-count="100"  
  waveform-folder=""  
>
```

4.4 SDR Manager

This element specifies parameters of the Synthesis Details Record (SDR) manager.

Attributes

Name	Unit	Description
save-records	Boolean	Specifies whether to save recognition details records or not.
purge-existing	Boolean	Specifies whether to delete existing records on start-up.
max-file-age	Time interval [min]	Specifies a time interval in minutes after expiration of which a record is deleted. Set 0 for infinite.
max-file-count	Integer	Specifies the max number of records to store. If reached, the oldest record is deleted. Set 0 for infinite.
record-folder	Dir path	Specifies a folder to store recognition details records in. Defaults to <code>\${UniMRCPIInstallDir}/var</code> .

Parent

< umsyandexss >

Children

None.

Example

The example below defines a typical utterance manager having the default parameters set.

```
<sdr-manager
  save-records="false"
  purge-existing="false"
  max-file-age="60"
  max-file-count="100"
  waveform-folder=""
/>
```

4.5 Monitoring Agent

This element specifies parameters of the monitoring agent.

Attributes

Name	Unit	Description
refresh-period	Time interval [sec]	Specifies a time interval in seconds used to periodically refresh usage details. See <usage-refresh-handler>.

Parent

<umspyandexss>

Children

<usage-change-handler>

<usage-refresh-handler>

Example

The example below defines a monitoring agent with usage change and refresh handlers.

```
<monitoring-agent refresh-period="60">  
  <usage-change-handler>  
    <log-usage enable="true" priority="NOTICE"/>  
  </usage-change-handler>  
  
  <usage-refresh-handler>  
    <dump-channels enable="true" status-file="umspyandexss-channels.status"/>  
  </usage-refresh-handler >  
  
</monitoring-agent>
```

4.6 Usage Change Handler

This element specifies an event handler called on every usage change.

Attributes

None.

Parent

```
<monitoring-agent>
```

Children

```
<log-usage>  
<update-usage>  
<dump-channels>
```

Example

This is an example of the usage change event handler.

```
<usage-change-handler>  
  <log-usage enable="true" priority="NOTICE"/>  
  <update-usage enable="false" status-file="umsyandexss-usage.status"/>  
  <dump-channels enable="false" status-file="umsyandexss-channels.status"/>  
</usage-change-handler>
```

4.7 Usage Refresh Handler

This element specifies an event handler called periodically to update usage details.

Attributes

None.

Parent

```
<monitoring-agent>
```

Children

```
<log-usage>  
<update-usage>  
<dump-channels>
```

Example

This is an example of the usage change event handler.

```
<usage-refresh-handler>  
  <log-usage enable="true" priority="NOTICE"/>  
  <update-usage enable="false" status-file="umsyandexss-usage.status"/>  
  <dump-channels enable="false" status-file="umsyandexss-channels.status"/>  
</usage-refresh-handler>
```

4.8 License Server

This element specifies parameters used to connect to the license server.

Attributes

Name	Unit	Description
enable	Boolean	Specifies whether the use of license server is enabled or not. If enabled, the license-file attribute is not honored.
server-address	String	Specifies the IP address or host name of the license server.
certificate-file	File path	Specifies the client certificate used to connect to the license server. File name may include patterns containing a '*' sign. If multiple files match the pattern, the most recent one gets used.
ca-file	File path	Specifies the certificate authority used to validate the license server.
channel-count	Integer	Specifies the number of channels to check out from the license server. If not specified or set to 0, either all available channels or a pool of channels will be checked based on the configuration of the license server.

Parent

<umsyandexss>

Children

None.

Example

The example below defines a typical configuration which can be used to connect to a license server located, for example, at 10.0.0.1.

```
<license-server
  enable="true"
  server-address="10.0.0.1"
  certificate-file="unilic_client_*.cert"
  ca-file="unilic_ca.crt"
/>
```

For further reference to the license server, visit

<http://unimrcp.org/licserver>

5 Configuration Steps

This section outlines common configuration steps.

5.1 Using Default Configuration

The default configuration should be sufficient for the general use.

5.2 Specifying Folder ID

The Yandex SpeechKit folder identifier must be set in the in the configuration file *umsyandexss.xml*.

5.3 Specifying Synthesis Language

Synthesis language can be specified by the client per MRCP session by means of the header field *Speech-Language* set in a *SET-PARAMS* or *SPEAK* request. Otherwise, the parameter *language* set in the configuration file *umsyandexss.xml* is used. The parameter defaults to *en-US*.

5.4 Specifying Sampling Rate

Sampling rate is determined based on the SDP negotiation. Refer to the configuration guide of the UniMRCP server on how to specify supported encodings and sampling rates to be used in communication between the client and server. Either 8 or 16 kHz can be used.

5.5 Specifying Voice Parameters

The default voice name can be specified from the configuration file *umsyandexss.xml* using the *voice-name* attribute of the *synth-settings* element.

The voice name and gender can be specified by the MRCP client in *SET-PARAMS* and *SPEAK* requests.

- Voice-Name

This is an optional parameter indicating the name of the voice to use for synthesis.

5.6 Specifying Prosody Parameters

The following prosody parameters can be specified by the MRCP client in *SET-PARAMS* and *SPEAK* requests.

- Prosody-Rate

This is an optional parameter indicating the speaking rate, which can be set to one of the following labels: *x-slow*, *slow*, *medium*, *fast*, *x-fast*, *default*.

- Prosody-Volume

This is an optional parameter indicating the speaking volume, which can be set to one of the following labels: *silent*, *x-soft*, *soft*, *medium*, *loud*, *x-loud*, *default*.

5.7 Specifying Speech Data

Speech data can be specified by the MRCP client in *SPEAK* requests using one of the following content type:

- plain/text

5.8 Maintaining Waveforms

Collection of waveforms is not required for regular operation and is disabled by default. However, enabling this functionality allows to save synthesized speech received from the Yandex SpeechKit service and later listen to them offline.

The relevant settings can be specified via the element *waveform-manager*.

- save-waveforms

Utterances can optionally be recorded and stored if the configuration parameter *save-waveforms* is set to true.

- purge-existing

This parameter specifies whether to delete existing waveforms on start-up.

- max-file-age

This parameter specifies a time interval in minutes after expiration of which a waveform is deleted. If set to 0, there is no expiration time specified.

- max-file-count

This parameter specifies the maximum number of waveforms to store. If the specified number is reached, the oldest waveform is deleted. If set to 0, there is no limit specified.

- waveform-folder

This parameter specifies a path to the directory used to store waveforms in. The directory defaults to *\${UniMRCPInstallDir}/var*.

5.9 Maintaining Synthesis Details Records

Collection of synthesis details records (SDR) is not required for regular operation and is disabled by default. However, enabling this functionality allows to store details of each synthesis attempt in a separate file and analyze them later offline. The SDRs are stored in the JSON format.

The relevant settings can be specified via the element *sdr-manager*.

- save-records

This parameter specifies whether to save synthesis details records or not.

- `purge-existing`

This parameter specifies whether to delete existing records on start-up.

- `max-file-age`

This parameter specifies a time interval in minutes after expiration of which a record is deleted. If set to 0, there is no expiration time specified.

- `max-file-count`

This parameter specifies the maximum number of records to store. If the specified number is reached, the oldest record is deleted. If set to 0, there is no limit specified.

- `record-folder`

This parameter specifies a path to the directory used to store records in. The directory defaults to `${UniMRCPIInstallDir}/var`.

6 Monitoring Usage Details

The number of in-use and total licensed channels can be monitored in several alternate ways. There is a set of actions which can take place on certain events. The behavior is configurable via the element *monitoring-agent*, which contains two event handlers: *usage-change-handler* and *usage-refresh-handler*.

While the *usage-change-handler* is invoked on every acquisition and release of a licensed channel, the *usage-refresh-handler* is invoked periodically on expiration of a timeout specified by the attribute *refresh-period*.

The following actions can be specified for either of the two handlers.

6.1 Log Usage

The action *log-usage* logs the following data in the order specified.

- The number of currently in-use channels.
- The maximum number of channels used concurrently.
- The total number of licensed channels.

The following is a sample log statement, indicating 0 in-use, 0 max-used and 2 total channels.

```
[NOTICE] YandexSS Usage: 0/0/2
```

6.2 Update Usage

The action *update-usage* writes the following data to a status file *umsyandexss-usage.status*, located by default in the directory `${UniMRCPIInstallDir}/var/status`.

- The number of currently in-use channels.
- The maximum number of channels used concurrently.
- The total number of licensed channels.
- The current status of the license permit.

The following is a sample content of the status file.

```
in-use channels: 0  
max used channels: 0  
total channels: 2  
total channels: 2
```

6.3 Dump Channels

The action *dump-channels* writes the identifiers of in-use channels to a status file *umsyandexss-channels.status*, located by default in the directory *\${UniMRCPIInstallDir}/var/status*.

7 Usage Examples

7.1 Plain Text

This examples demonstrates how to perform speech synthesis by using a SPEAK request with a plain text content.

C->S:

```
MRCP/2.0 155 SPEAK 1
Channel-Identifier: 85667d0efbf95345@speechsynth
Content-Type: text/plain
Voice-Age: 28
Content-Length: 20
```

Welcome to Uni MRCP.

S->C:


```
MRCP/2.0 83 1 200 IN-PROGRESS
Channel-Identifier: 85667d0efbf95345@speechsynth
```

S->C:

```
MRCP/2.0 122 SPEAK-COMPLETE 1 COMPLETE
Channel-Identifier: 85667d0efbf95345@speechsynth
Completion-Cause: 000 normal
```

8 Sequence Diagram

The following sequence diagram outlines common interactions between all the main components involved in a typical synthesis session performed over MRCPv2.



9 References

9.1 Yandex SpeechKit

- [Text to Speech API](#)
- [Authentication](#)

9.2 Specifications

- [Speech Synthesizer Resource](#)